

DIB01CB2310A

Carlo Gavazzi Monitoring Relay Over/Under Current via Int-Shnt
1-10A ACDC and 115-230VAC 1CO



Component type	Current monitoring relay
Range	V//I/PH/PF Monitoring
Model	N/A
Alternative	705102402032

The Carlo Gavazzi range of monitoring relays are designed for the detection of phase loss and incorrect phase sequence to over/under current and voltage. Suitable for use in a wide range of applications that require protection against people, fire, earth current leakage, or incorrect mains or cable connections. Installation is easy with front dials and DIP switches.

ELECTRICAL

Current measuring range	1-10 A
External current transformer	Yes
Single-phase under current possible	Yes
Single-phase over current possible	Yes
Rated frequency	45-65 Hz
Contains function DC-voltage under current	Yes
Contains function DC-voltage over current	Yes
Number of contacts as change-over contact	1
Rated operation current Ie	8 A
Rated operation current Ie at AC-15, 230 V	2.5 A
Rated operation current Ie at DC-12, 24 V	5 A
Rated operation current Ie at DC-13, 24 V	2.5 A
Voltage type for actuating	AC
Control supply voltage AC, 2nd input	115 V
Control supply voltage Us at AC 50HZ	230 V
Over voltage category	III
Type of electric connection	Screw connection
Min. adjustable delay-on energization time	1 s
Max. permitted delay-on energization time	6 s

CONSTRUCTION

Material contact	Silver tin-oxide
Suitable for DIN rail mounting	Yes

DIMENSIONS

IP rating	IP20
Height	83.5 mm
Width	22.5 mm
Depth	99.5 mm

DIB01CB2310A

Carlo Gavazzi Monitoring Relay Over/Under Current via Int-Shnt
1-10A ACDC and 115-230VAC 1CO



MONITORING RELAYS



DIMENSIONS

Weight


0.15 kg

ENVIRONMENT

Storage temperature

-30...80 °C

DIMENSIONAL DIAGRAM



Models

DIA01
DIB01
DIB02
DUA01
DUB01
DUB02
DPA01
DPB01
DPB02
DFB01