TCD1X160200CMX

Carlo Gavazzi EM270 Quick Fit 3 Phase Solid Core CT 160A 15.5 x 25mm Holes 25mm Centres 2000mm Cable

3 PHASE METERS



Component type	Current transformer
Range	EM270/EM271
Model	N/A
Product status	Discontinued

The Carlo Gavazzi Quick-fit CT Dual Monitoring Meters provide a comprehensive and accurate measurement of energy consumption for multi-load monitoring applications.

ELECTRICAL	Primary rated current	160 A
CONSTRUCTION	Current transformer type	Solid core
	Material housing	Other
	Model	3-phase current converter set
	Number of primary inputs	3
ENVIRONMENT	Storage temperature	-30…70 °C

Published on 18 June 2026